

Scheduling and Codeword Length Optimization in Time Varying Wireless Networks

Mehdi Ansari Sadrabadi, Alireza Bayesteh and Amir K. Khandani

Coding & Signal Transmission Laboratory(www.cst.uwaterloo.ca)

Dept. of Elec. and Comp. Eng., University of Waterloo

Waterloo, ON, Canada, N2L 3G1

Tel: 519-884-8552, Fax: 519-888-4338

e-mail: {mehdi, alireza, khandani}@cst.uwaterloo.ca

Abstract—In this paper, a downlink scenario in which a single-antenna base station communicates with K single antenna users, over a time-correlated fading channel, is considered. It is assumed that channel state information is perfectly known at each receiver, while the statistical characteristics of the fading process and the fading gain at the beginning of each frame are known to the transmitter. By evaluating the random coding error exponent of the time-correlated fading channel, we show that there is an optimal codeword length which maximizes the throughput. We examine the throughput of the conventional scheduling that transmits to the user with the maximum signal to noise ratio using both fixed length codewords and variable length codewords. Although optimizing the codeword length improves the performance, it is shown that using the conventional scheduling, a gap of $\Omega(\sqrt{\log \log \log K})$ exists between the achievable throughput and the maximum possible throughput of the system. We propose a simple scheduling that considers both the signal to noise ratio and the channel time variation. We show that by using this scheduling, the gap between the achievable throughput and the maximum throughput of the system approaches zero.

I. INTRODUCTION

In wireless networks, diversity is a means to combat the time varying nature of the communication link. Conventional diversity techniques over point-to-point links, such as spatial diversity and frequency diversity are widely used and offer performance improvements. In multiuser wireless systems, there exists another form of diversity, called *multiuser diversity* [1]. In a broadcast channel where users have independent fading and feedback their signal to noise ratio (SNR) to the base station (BS), system throughput is maximized by transmitting to the user with the strongest SNR [1], [2].

Multiuser diversity was introduced first by Knopp and Humblet [3]. It is shown that the optimal transmission strategy in the uplink of multiuser systems using power control is to only let the user with the largest SNR transmit. A similar result is shown to be valid for the downlink [4]. Multiuser diversity underlies much of the recent works for downlink scheduling [5]–[8] as in Qualcomm's high data rate (HDR) system [9], [10]. In [8], [11], the opportunistic scheduling is based on the highest data rate which can be reliably transmitted to each user. Distributed scheduling is proposed in an uplink scenario, where full channel state information (CSI) is not required at the transmitter [12], [13]. Multiuser diversity has also been studied in the context of multiple antenna systems [1], [14]

and ad-hoc networks [15].

In wireless networks, the rate of channel variations is characterized by maximum Doppler frequency which is proportional to the velocity. Utilizing multiuser diversity in such environments needs to be revisited since the throughput depends not only on the received SNR, but also on how fast the channel varies over time.

In this paper, we consider a broadcast channel in which a BS transmits data to a large number of users in a time correlated flat fading environment. It is assumed that CSI is perfectly known to the receivers, while BS only knows the statistical characteristics of the fading process for all the users (which is assumed to be constant during a long period). Moreover, each user feeds back its channel gain to the BS at the beginning of each frame. Based on this information, BS selects a single user for transmission in each frame, in order to maximize the throughput. For the case of Additive White Gaussian Noise (AWGN) or block fading, it is well known that increasing the codeword length results in improving the achievable throughput. However, in a time varying channel, it is not possible to obtain arbitrary small error probabilities by increasing the codeword length. In fact, increasing the codeword length also results in increasing the fading fluctuations over the frame, and consequently, the throughput will decrease. Therefore, it is of interest to find the optimum codeword length which maximizes the throughput.

In this paper, a downlink scenario in which a single-antenna base station communicates with K single antenna users, over a time-correlated fading channel, is considered. We analyze different user selection strategies; i) the BS transmits data to the user with the strongest SNR using fixed length codewords (conventional multiuser scheduling), ii) the BS transmits data to the user with the strongest SNR using variable length codewords, and iii) the BS transmits data to the user that achieves the maximum throughput using variable length codewords. We show that in all cases the achievable throughput scales as $\log \log K$. Moreover, in cases (i) and (ii), the gap between the achievable throughput and the maximum throughput scales as $\sqrt{\log \log \log K}$, while in case (iii), this gap approaches zero.

The rest of the paper is organized as follows. In Section II, the model of time-correlated fading channel is described. In Section III, different user selection strategies are discussed and

the corresponding throughput of the system is derived for each strategy, for $K \rightarrow \infty$. Finally, in Section IV, we conclude the paper.

Throughout this paper, $\mathbb{E}\{\cdot\}$ and $\text{var}\{\cdot\}$ represents the expectation and variance, respectively, “log” is used for the natural logarithm, and rate is expressed in *nats*. For any functions $f(N)$ and $g(N)$, $f(N) = O(g(N))$ is equivalent to $\lim_{N \rightarrow \infty} \left| \frac{f(N)}{g(N)} \right| < \infty$, $f(N) = o(g(N))$ is equivalent to $\lim_{N \rightarrow \infty} \left| \frac{f(N)}{g(N)} \right| = 0$, $f(N) = \omega(g(N))$ is equivalent to $\lim_{N \rightarrow \infty} \frac{f(N)}{g(N)} = \infty$, and $f(N) = \Omega(g(N))$ is equivalent to $\lim_{N \rightarrow \infty} \frac{f(N)}{g(N)} = c$, where $0 < c < \infty$.

II. SYSTEM MODEL

The channel of any given user is modeled as a time-correlated fading process. It is assumed that the channel gain is constant over each channel use (symbol) and varies from symbol to symbol, following a Markovian random process. Assume that the fading gain of k^{th} user is $\mathbf{h}_k = [h_{1,k}, \dots, h_{N_k,k}]^T$ where $h_{i,k}$, $1 \leq i \leq N_k$ are complex Gaussian random variables with zero mean and unit variance and N_k is the codeword length of the k^{th} user. The received signal for the k^{th} user is given by

$$\mathbf{r}_k = \mathbf{S}_k \mathbf{h}_k + \mathbf{n}_k, \quad (1)$$

where $\mathbf{S}_k = \text{diag}(s_{1,k}, s_{2,k}, \dots, s_{N_k,k})$ is the transmitted codeword with the power constraint¹ $\mathbb{E}\{|s_{i,k}|^2\} \leq P$, and \mathbf{n}_k is AWGN with zero mean and covariance matrix \mathbf{I} . Assume that $h_{0,k}$ is the fading gain at the time instant before \mathbf{S}_k is transmitted. The sequence $u_{i,k} = |h_{i,k}|$, $0 \leq i \leq N_k$, is assumed to be a stationary ergodic chain with the following probability density function [16]:

$$f_{u_{0,k}}(u) = \begin{cases} 2ue^{-u^2} & u \geq 0 \\ 0 & \text{otherwise} \end{cases}, \quad (2)$$

$$f(u_{1,k}, u_{2,k}, \dots, u_{N_k,k} | u_{0,k}) = \prod_{i=1}^{N_k} q_k(u_{i,k} | u_{i-1,k}), \quad (3)$$

where,

$$q_k(u|v) = \begin{cases} \frac{2u}{1-\alpha_k^2} \exp\left(-\frac{u^2 + \alpha_k^2 v^2}{1-\alpha_k^2}\right) \mathcal{I}_0\left(\frac{2\alpha_k uv}{1-\alpha_k^2}\right) & u \geq 0 \\ 0 & \text{otherwise} \end{cases}$$

in which $0 < \alpha_k < 1$ describes the channel correlation coefficient of the k^{th} user. It is assumed that α_k , $1 \leq k \leq K$, are i.i.d. random variables with uniform distribution which remain fixed during the entire transmission, and $\mathcal{I}_0(\cdot)$ denotes the modified Bessel function of order zero. It is assumed that CSI is perfectly known at each receiver, while the statistical characteristics of the fading process and $u_{0,k}$, $1 \leq k \leq K$ are known to the transmitter.

¹Obviously, for maximizing the throughput, the power constraint translates to $\mathbb{E}\{|s_{i,k}|^2\} = P$.

III. THROUGHPUT ANALYSIS

In this section, we derive the achievable throughput of the system in the asymptotic case of $K \rightarrow \infty$. We define the k^{th} user's throughput per channel use, denoted by T_k , as

$$T_k \triangleq R_k(1 - p_e(k)), \quad (4)$$

where R_k is the transmitted rate per channel use and $p_e(k)$ is the frame error probability for this user. Using the concept of random coding error exponent [17], $p_e(k)$ can be upper-bounded as

$$p_e(k) \leq \inf_{0 \leq \rho \leq 1} e^{-N(E_k(\rho) - \rho R_k)}. \quad (5)$$

For simplicity of analysis, we use this upper bound in evaluating the throughput. This bound is tight for rates close to the capacity as used in [18]–[20].

Assuming $s_{i,k}$, $1 \leq i \leq N_k$, are Gaussian and i.i.d., it is shown that the random coding error exponent for the k^{th} user, $E_k(\rho)$, is given by [20],

$$E_k(\rho) = -\frac{1}{N_k} \log \mathbb{E}_{\mathbf{u}_k} \left\{ \prod_{i=1}^{N_k} \left(\frac{1}{1 + \frac{P}{1+\rho} u_{i,k}^2} \right)^\rho \right\}. \quad (6)$$

where $\mathbf{u}_k = [u_{1,k}, \dots, u_{N_k,k}]$.

In the following, we assume that $u_{0,k} \gg 1$. Since in strategies introduced in this work, a user is selected if the corresponding initial fading gain is maximum or above a certain threshold, this assumption is valid when the number of users is large.

Theorem 1 *For the channel model described in the previous section, and assuming $u_{0,k}$ is known, we have [21]*

$$E_k(\rho) = \frac{1}{N_k} \sum_{i=1}^{N_k} \rho \log \left(1 + \frac{P u_{0,k}^2 \alpha_k^{2i}}{(1+\rho)} \right) + O\left(\frac{1}{\sqrt{u_{0,k}}}\right). \quad (7)$$

Minimizing (5) is equivalent to maximizing $E_k(\rho) - \rho R_k$. Noting (7), for large values of $u_{0,k}$, we have

$$\begin{aligned} E_k(\rho) - \rho R_k &= \frac{1}{N_k} \sum_{i=1}^{N_k} \rho \log \left(1 + \frac{P u_{0,k}^2 \alpha_k^{2i}}{(1+\rho)} \right) - \rho R_k \\ &= \rho [\log(P u_{0,k}^2) + (N_k + 1) \log(\alpha_k) \\ &\quad - \log(\rho + 1) - R_k]. \end{aligned} \quad (8)$$

It is easy to show that ρ_k^{opt} which maximizes (8) for large values of $u_{0,k}$ is

$$\begin{aligned} \log(1 + \rho_k^{\text{opt}}) + \frac{\rho_k^{\text{opt}}}{1 + \rho_k^{\text{opt}}} &= \beta_k, \quad \beta_k < \log(2) + \frac{1}{2} \\ \rho_k^{\text{opt}} &= 1, \quad \beta_k \geq \log(2) + \frac{1}{2} \end{aligned} \quad (9)$$

where

$$\beta_k = \log(P u_{0,k}^2) + (N_k + 1) \log(\alpha_k) - R_k. \quad (10)$$

Using (4), (5), (7) and (8), we have

$$\begin{aligned} T_k &= R_k \left[1 - e^{-N_k (E_k(\rho_k^{\text{opt}}) - \rho_k^{\text{opt}} R_k)} \right] \\ &= R_k \left[1 - e^{-\rho_k^{\text{opt}} N_k \left(\log\left(\frac{P u_{0,k}^2}{\rho_k^{\text{opt}} + 1}\right) + (N_k + 1) \log(\alpha_k) - R_k \right)} \right]. \end{aligned} \quad (11)$$

It is easy to show that T_k is a concave function of variables R_k and N_k , and the values of R_k and N_k which maximize the throughput (R_k^{opt} and N_k^{opt}) satisfy the following equations²:

$$R_k^{\text{opt}} = \log(P u_{0,k}^2) + (2N_k^{\text{opt}} + 1) \log(\alpha_k) - \log(\rho_k^{\text{opt}} + 1), \quad (12)$$

$$N_k^{\text{opt}} = \sqrt{\frac{\log(1 + \rho_k^{\text{opt}} N_k^{\text{opt}} R_k^{\text{opt}})}{\rho_k^{\text{opt}} \log(\alpha_k^{-1})}}. \quad (13)$$

It follows that $N_k^{\text{opt}} \rightarrow \infty$ and $R_k^{\text{opt}} \rightarrow \infty$ as $u_{0,k} \rightarrow \infty$. Substituting (12) in (10), we have

$$\beta_k = N_k^{\text{opt}} \log(\alpha_k^{-1}) + \log(\rho_k^{\text{opt}} + 1). \quad (14)$$

From (9) and (14), it is concluded that

$$\rho_k^{\text{opt}} = \begin{cases} \frac{N_k^{\text{opt}} \log(\alpha_k^{-1})}{1 - N_k^{\text{opt}} \log(\alpha_k^{-1})} & N_k^{\text{opt}} \log(\alpha_k^{-1}) < \frac{1}{2} \\ 1 & N_k^{\text{opt}} \log(\alpha_k^{-1}) \geq \frac{1}{2} \end{cases} \quad (15)$$

Noting (12) and (15), for $\alpha_k = 1$, we have $\rho_k^{\text{opt}} = 0$ and $R_k^{\text{opt}} = \log(P u_{0,k}^2)$ which corresponds to the capacity of a quasi-static fading channel (for large values of channel gain $u_{0,k}$).

In the following, we obtain the asymptotic throughput of the k^{th} user. Since there are two regions for ρ_k^{opt} as shown in (15), we calculate the closed form formula of the throughputs of these two cases separately.

- ($\rho_k^{\text{opt}} = 1$): The corresponding asymptotic throughput is obtained by substituting (12) and (13) in (11) as follows:

$$\begin{aligned} T_k &= \log\left(\frac{P u_{0,k}^2}{2}\right) - 2 \sqrt{\log(\alpha_k^{-1}) \log \log\left(\frac{P u_{0,k}^2}{2}\right)} \times \\ &\quad \left(1 + O\left(\frac{\log \log \log(u_{0,k})}{\log \log(u_{0,k})}\right)\right). \end{aligned} \quad (16)$$

From (13), the optimum codeword length scales as follows:

$$N_k^{\text{opt}} \sim \sqrt{\frac{\log \log(P u_{0,k}^2)}{\log \alpha^{-1}}}. \quad (17)$$

Note that if α_k is fixed and $\alpha_k \neq 1$, then $N_k^{\text{opt}} \log(\alpha_k^{-1}) \geq \frac{1}{2}$ for large values of $u_{0,k}$ and (16) is applicable.

- ($\rho_k^{\text{opt}} < 1$): We limit the calculation of the throughput to the assumption of $N_k^{\text{opt}} \log(\alpha_k^{-1}) \sim o(1)$ to be able to

derive the following closed form formula by using (11) and (15).

$$\begin{aligned} T_k &= \log(P u_{0,k}^2) - 2 \sqrt{\log(\alpha_k^{-1}) \log \log(P u_{0,k}^2)} \times \\ &\quad \left(1 + O\left(\frac{\log \log \log(u_{0,k})}{\log \log(u_{0,k})}\right)\right) - o(1). \end{aligned} \quad (18)$$

The corresponding optimum codeword length scales as follows:

$$N_k^{\text{opt}} \sim \sqrt[3]{\frac{\log \log(P u_{0,k}^2)}{(\log \alpha^{-1})^2}}. \quad (19)$$

As we will see later, this special case is sufficient to accomplish the calculation required in the rest of the paper.

From the above equations, it is concluded that the throughput not only depends on the initial fading gain, $u_{0,k}$, but also on the fading correlation coefficient. Moreover, the throughput is an increasing function of the channel correlation coefficient.

In the following, we introduce three scheduling strategies in order to maximize the throughput; i) Traditional scheduling in which the user with the largest channel gain (SNR-based scheduling) is selected and the codeword length is assumed to be fixed. ii) SNR-based scheduling with optimized codeword length regarding the channel condition of the selected user, and iii) Scheduling which exploits both the channel gain and the channel correlation coefficient of the users. The asymptotic throughput of the system is derived under each strategy for $K \rightarrow \infty$.

A. Strategy I: SNR-based scheduling with fixed codeword length

The BS transmits to the user with the maximum initial fading gain. The codeword length of all users is fixed, i.e., $N_1 = N_2 = \dots = N_K = N$. The codeword length N is selected such that the throughput of the system is maximized. The BS adapts the data rate to maximize the throughput of the selected user.

Theorem 2 *The asymptotic throughput of the system under Strategy I scales as [21]*

$$\bar{T}_1 \sim \log\left(\frac{P \log K}{2}\right) - 2 \sqrt{\mathbb{E}\{\log(\alpha^{-1})\} \log \log \log K}, \quad (20)$$

as $K \rightarrow \infty$.

B. Strategy II: SNR-based scheduling with adaptive codeword length

In this scheme, the BS transmits to the user with the maximum initial fading gain. The rate and codeword length are selected to maximize the corresponding throughput.

²Note that we have relaxed the condition of N_k being integer. However, since the optimizing N_k tends to infinity as $K \rightarrow \infty$, this assumption does not affect the result.

Theorem 3 Assuming $K \rightarrow \infty$, the asymptotic throughput of the system under Strategy II scales as follows:

$$\bar{T}_2 \sim \log\left(\frac{P \log K}{2}\right) - 2\mathbb{E}\{\sqrt{\log(\alpha^{-1})}\} \sqrt{\log \log\left(\frac{P \log K}{2}\right)}. \quad (21)$$

Proof: The throughput of the system can be written as

$$\bar{T}_2 = \bar{T}_{2|\mathcal{B}} \Pr\{\mathcal{B}\} + \bar{T}_{2|\mathcal{B}^C} \Pr\{\mathcal{B}^C\}, \quad (22)$$

where \mathcal{B} represents the event that $\rho^{\text{opt}} = 1$, $\bar{T}_{2|\mathcal{B}}$ denotes the throughput conditioned on \mathcal{B} , and $\bar{T}_{2|\mathcal{B}^C}$ is the throughput of the system conditioned on \mathcal{B}^C , the complement of \mathcal{B} . Using (16), we can write

$$\bar{T}_{2|\mathcal{B}} = \mathbb{E}\left\{\log\left(\frac{Pv}{2}\right) - 2\sqrt{\log(\alpha^{-1}) \log \log\left(\frac{Pv}{2}\right)} \middle| \mathcal{B}\right\},$$

where $v = \max_{1 \leq k \leq K} v_k$, and α is the channel correlation coefficient of the selected user. Noting that $v \sim \log K + O(\log \log K)$ with probability one, and v and α are independent, we have

$$\begin{aligned} \bar{T}_{2|\mathcal{B}} &\sim \log\left(\frac{P \log K}{2}\right) \\ &- 2\mathbb{E}\left\{\sqrt{\log(\alpha^{-1})} \middle| \mathcal{B}\right\} \sqrt{\log \log\left(\frac{P \log K}{2}\right)}. \end{aligned} \quad (23)$$

Using (15) and (17), we can write

$$\mathcal{B} \cong \sqrt{\log(\alpha^{-1})} \sqrt{\log \log \log K} \geq \frac{1}{2}. \quad (24)$$

Uniform distribution for α results in exponential distribution for $X \triangleq \log(\alpha^{-1})$, i.e., $f_X(x) = e^{-x}u(x)$. Let us define $\epsilon \triangleq \frac{1}{4 \log \log \log K} \cdot \Pr\{\mathcal{B}\}$ can be derived as follows:

$$\Pr\{\mathcal{B}\} = \Pr\{\log(\alpha^{-1}) \geq \epsilon\} = e^{-\epsilon}. \quad (25)$$

Using (25), we have

$$\begin{aligned} \mathbb{E}\left\{\sqrt{\log(\alpha^{-1})} \middle| \mathcal{B}\right\} &= \frac{\int_{\epsilon}^{\infty} \sqrt{x} e^{-x} dx}{\Pr\{\mathcal{B}\}} \\ &\sim \mathbb{E}\{\sqrt{\log(\alpha^{-1})}\} (1 + O(\epsilon)). \end{aligned} \quad (26)$$

Similarly, we can write

$$\begin{aligned} \mathbb{E}\left\{\sqrt{\log(\alpha^{-1})} \middle| \mathcal{B}^C\right\} &= \frac{\int_0^{\epsilon} \sqrt{x} e^{-x} dx}{\Pr\{\mathcal{B}^C\}} \\ &\sim O(\sqrt{\epsilon}). \end{aligned} \quad (27)$$

Using (11), $\bar{T}_{2|\mathcal{B}^C}$ can be written as

$$\begin{aligned} \bar{T}_{2|\mathcal{B}^C} &\gtrsim \log\left(\frac{P \log K}{2}\right) - \mathbb{E}\{\log(\alpha^{-1})|\mathcal{B}^C\} - 2 \\ &\stackrel{(27)}{\gtrsim} \log\left(\frac{P \log K}{2}\right) - 2 - O(\sqrt{\epsilon}), \end{aligned} \quad (28)$$

Moreover, using (11) and noting that $v \sim \log K$ with probability one, we have

$$\bar{T}_{2|\mathcal{B}^C} \lesssim \log(P \log K). \quad (29)$$

Substituting (23), (28) and (29) in (22) and noting (25) and (26), the result of the theorem is obtained.

Remark 1- Since $\mathbb{E}\{\sqrt{x}\} \leq \sqrt{\mathbb{E}\{x\}}$, for $x > 0$, it is concluded that the achievable rate of Strategy II is higher than that of Strategy I. More precisely,

$$\bar{T}_2 - \bar{T}_1 \sim 2 \left(\sqrt{\mathbb{E}\{\log(\alpha^{-1})\}} - \mathbb{E}\{\sqrt{\log(\alpha^{-1})}\} \right) \times \sqrt{\log \log \log K}. \quad (30)$$

For the case of uniform distribution for α , we have

$$\bar{T}_2 - \bar{T}_1 \sim 0.228 \sqrt{\log \log \log K}. \quad (31)$$

Remark 2- Although $\lim_{K \rightarrow \infty} \frac{\bar{T}_1}{\bar{T}_{\max}} = \lim_{K \rightarrow \infty} \frac{\bar{T}_2}{\bar{T}_{\max}} = 1$, where $\bar{T}_{\max} \sim \log(P \log K)$ is the maximum achievable throughput for a quasi-static fading channel [22], there exists a gap of $\Omega(\sqrt{\log \log \log K})$ between the achievable throughput of Strategies I and II, and the maximum throughput. As we show later, this gap is due to the fact that the channel correlation coefficients of the users are not considered in the scheduling. In fact, this gap approaches zero by exploiting the channel correlation, which is discussed in Strategy III.

C. Strategy III: Scheduling based on both SNR and channel correlation coefficient with adaptive codeword length

To maximize the throughput of the system, the user which maximizes the expression in (11) should be serviced. Here, for simplicity of analysis, we propose a sub-optimum scheduling that considers the effect of both SNR and channel correlation in the user selection. In this strategy, each user is required to feed back its initial fading gain only if it is greater than a pre-determined threshold $\sqrt{\Theta}$, where Θ is a function of the number of users. Among these users, the BS selects the one with the maximum channel correlation coefficient. The data rate and codeword length are selected to maximize the corresponding throughput. The following theorem gives the system throughput under this strategy.

Theorem 4 Using Strategy III, with Θ satisfying

$$\log K - o(\log K) \lesssim \Theta \lesssim \log K - \log \log K - \omega(1), \quad (32)$$

the throughput of the system scales as

$$\bar{T}_3 \gtrsim \log(P \log K) - o(1). \quad (33)$$

Proof: Define $\mathcal{S} \triangleq \{k | v_k \geq \Theta\}$ and $\alpha_{\max} \triangleq \max_{k \in \mathcal{S}} \alpha_k$. Let v be the squared initial fading gain of the user corresponding to α_{\max} . We define the event \mathcal{G} as follows:

$$\mathcal{G} \equiv N^{\text{opt}} \log(\alpha_{\max}^{-1}) \sim o(1), \quad (34)$$

where N^{opt} is the corresponding codeword length as computed from (13). Using (18) and (34), we can write

$$\bar{T}_3 \geq \Pr\{\mathcal{G}\} \mathbb{E}\{\mathcal{T}_3(v, \alpha_{\max}) | \mathcal{G}\}, \quad (35)$$

where following (18),

$$\begin{aligned} \mathbb{E}\{\mathcal{T}_3(v, \alpha_{\max}) | \mathcal{G}\} &\simeq \mathbb{E}\left\{\log(Pv) - 2\sqrt{\log(\alpha_{\max}^{-1})} \times \right. \\ &\quad \left. \sqrt{\log \log(Pv)} - o(1)\right\}. \end{aligned} \quad (36)$$

Noting that $\{\mathcal{T}_3(v, \alpha_{\max})|\mathcal{G}\}$ in (36) is an increasing function of v , we have

$$\begin{aligned}\mathbb{E}\{\mathcal{T}_3(v, \alpha_{\max})|\mathcal{G}\} &\geq \log(P\Theta) - 2\mathbb{E}\{\sqrt[3]{\log(\alpha_{\max}^{-1})}\} \times \\ &\quad \sqrt[3]{\log \log(P\Theta)} - o(1) \\ &\geq \log(P\Theta) - 2\sqrt[3]{\mathbb{E}\{\log(\alpha_{\max}^{-1})\}} \times \\ &\quad \sqrt[3]{\log \log(P\Theta)} - o(1),\end{aligned}\quad (37)$$

where for large values of K , $\mathbb{E}\{\log(\alpha_{\max}^{-1})\}$ can be approximated as follows [21]:

$$\begin{aligned}\mathbb{E}\{\log(\alpha_{\max}^{-1})\} &\simeq \frac{1}{Ke^{-\Theta}} \left(1 + O\left(\frac{1}{Ke^{-\Theta}}\right)\right) \\ &+ e^{-Ke^{-\Theta}}(\Theta - \log K).\end{aligned}\quad (38)$$

Noting (38), for values of Θ satisfying (32), we have

$$\mathbb{E}\{\log(\alpha_{\max}^{-1})\} \log \log(\Theta) \sim o(1). \quad (39)$$

Using (37) and (39), we can write

$$\mathbb{E}\{\mathcal{T}_3(v, \alpha_{\max})|\mathcal{G}\} \geq \log(P \log K) - o(1). \quad (40)$$

To compute $\Pr\{\mathcal{G}\}$ defined in (34), we use Chebychev inequality.

$$\Pr\left\{|\mathcal{Z} - \mathbb{E}\{\mathcal{Z}\}| < \sqrt{\frac{1}{\log K} \text{var}\{\mathcal{Z}\}}\right\} > 1 - \frac{1}{\sqrt{\log K}}, \quad (41)$$

where $\mathcal{Z} = N^{\text{opt}} \log(\alpha_{\max}^{-1})$. Noting (19), (32) and (38), we have

$$\mathbb{E}\{N^{\text{opt}} \log(\alpha_{\max}^{-1})\} \leq o(1). \quad (42)$$

Also, noting (19), (32) and (38), we have

$$\text{var}\{N^{\text{opt}} \log(\alpha_{\max}^{-1})\} \lesssim O\left(\frac{\log \log \log K}{\log K}\right). \quad (43)$$

Substituting (42) and (43) in (41), we have

$$\begin{aligned}\Pr\left\{|N^{\text{opt}} \log(\alpha_{\max}^{-1}) - o(1)| < O\left(\frac{\log \log \log K}{\sqrt{\log K}}\right)\right\} \\ > 1 - \frac{1}{\sqrt{\log K}}.\end{aligned}\quad (44)$$

Noting (35), (40), and (44), the result of the theorem follows. ■

IV. CONCLUSION

A multiuser downlink communication over a time-correlated fading channel has been considered. We have proposed three scheduling schemes in order to maximize the throughput of the system. Assuming a large number of users in the system, we show that using SNR-based scheduling, a gap of $\Omega(\sqrt{\log \log \log K})$ exists between the achievable throughput and the maximum throughput of the system. We propose a simple scheduling considering both the SNR and channel correlation of the users. We show that the throughput of the proposed scheme reaches the maximum throughput of the system as the number of users tends to infinity.

REFERENCES

- [1] P. Viswanath, D.N.C. Tse, R. Laroia, "Opportunistic beamforming using dumb antennas," *IEEE Trans. Inform. Theory*, vol. 48, pp. 1277–1294, June 2002.
- [2] D. N. C. Tse and S. Hanly, "Multiaccess fading channels: Part i: Polymatroid structure, optimal resource allocation and throughput capacities," *IEEE Trans. Information Theory*, vol. 44, p. 27962815, Nov. 1998.
- [3] R. Knopp and P. A. Humblet, "Information capacity and power control in single-cell multiuser communications," *IEEE ICC '95*, vol. 1, pp. 331 – 335, June 1995.
- [4] D. Tse, "Optimal power allocation over parallel gaussian channels," in *Proc. Int. Symp. on Inform. Theory*, p. 27, June 1997.
- [5] R. Agrawal, A. Bedekar, R. La, and V. Subramanian, "A class and channel condition based weighted proportionally fair scheduler," in *Teletraffic Engineering in the Internet Era, Proc. Int. Teletraffic Congr.*, vol. ITC-17, p. 553565, Sept. 2001.
- [6] X. Liu, E. K. P. Chong, and N. B. Shroff, "Opportunistic transmission scheduling with resource-sharing constraints in wireless networks," *IEEE JSAC*, vol. 19, pp. 2053–2064, Oct. 2001.
- [7] Y. Liu and E. Knightly, "Opportunistic fair scheduling over multiple wireless channels," in *Proc. of 2003 IEEE INFOCOM*, p. 11061115, April 2003.
- [8] S. Borst and P. Whiting, "Dynamic rate control algorithms for HDR throughput optimization," in *Proc. IEEE INFOCOM 2001*, vol. 2, pp. 976–985, April 2001.
- [9] P. Bender, P. Black, M. Grob, R. Padovani, N. Sindhushayana, and A. Viterbi, "CDMA/HDR: A bandwidth efficient high-speed wireless data service for nomadic users," *IEEE Communications Magazine*, pp. 70–77, July 2000.
- [10] *CDMA 2000: High Rate Packet Data Air Interface Specification*. Std. TIA/EIA IS-856, Nov. 2000.
- [11] A. Jalali, R. Padovani, and R. Pankaj, "Data throughput of CDMA/HDR: A high efficiency, high data rate personal wireless system," in *Proc. IEEE Vehicular Tech. Conference*, vol. 3, pp. 1854–1858, May 2000.
- [12] X. Qin and R. Berry, "Exploiting multiuser diversity for medium access control in wireless networks," in *Proc. IEEE, INFOCOM*, pp. 1084–1094, 2003.
- [13] S. Shamai and E. Telatar, "Some information theoretic aspects of decentralized power control in multiple access fading channels," in *Proc. Inform. Theory and Networking Workshop*, 1999.
- [14] N. Sharma and L. H. Ozarow, "A study of opportunism for multiple-antenna systems," *IEEE Trans. Inform. Theory*, vol. 51, pp. 1804 – 1814, May 2005.
- [15] M. Grossglauser and D. Tse, "Mobility increases the capacity of ad-hoc wireless networks," in *Proc. INFOCOM 2001*, vol. 3, pp. 1360–1369, 2001.
- [16] A. N. Tzoufopoulou, "Convolutional codes for channels with fading," in *Proc. Inform. Transmission*, vol. 27, pp. 155–165, Oct. 1991.
- [17] R. G. Gallager, *Information theory and Reliable communication*. J. Wiley, New York, 1968.
- [18] R. A. Berry and R. G. Gallager, "Communication over fading channels with delay constraints," *IEEE Trans. Inform. Theory*, vol. 48, pp. 1135 – 1149, May 2002.
- [19] E. Telatar and R. G. Gallager, "Combining queueing theory with information theory for multiaccess," *IEEE J. Select. Areas Commun.*, vol. 13, pp. 963–969, May 1995.
- [20] G. Kaplan and S. Shamai, "Achievable performance over the correlated rician channel," *IEEE Trans. Commun.*, vol. 42, pp. 2967 – 2978, Nov. 1994.
- [21] Mehdi Ansari, Alireza Bayesteh and Amir K. Khandani, "Scheduling and codeword length optimization in time varying wireless networks," *To be submitted to IEEE Trans. Information Theory*.
- [22] M. Sharif and B. Hassibi, "On the capacity of mimo broadcast channels with partial side information," *IEEE Trans. Inform. Theory*, vol. 51, pp. 506 – 522, Feb. 2005.